


## MRE033

### MR 3G 2100 PRO

#### Description

The MR 3G PRO Repeater Kit is compatible with all high speed 3G 2100MHz data networks and effectively provides a strong and reliable phone signal in places with poor reception.

The Mini 3G kit comes with everything you need to boost coverage in your area! This product is simple to install, comes with 100% free technical support and is posted from the UK.



#### Key Features

- ✓ 3G 2100MHz Networks
- ✓ 60 dB gain
- ✓ Coverage up to 500 sq m
- ✓ High gain signal antenna
- ✓ Supports 50 simultaneous users
- ✓ Works with most UK and European providers
- ✓ Money back warranty

#### Working Principle



#### System Diagram



#### Package includes

- 1 x MR 3G 2100 PRO repeater
- 1 x External dual band signal antenna
- 1 x 10 m coax to connect to repeater
- 1 x AC/DC power supply
- 1 x Easy to follow installation manual

#### Electrical Specifications

Item	Uplink	Downlink
Frequency (GSM900)	1920-1990MHz	2110-2180MHz
Maximum Gain	≥ 55dB	≥ 60dB
Ripple in Band		≤ 5dB
Max. Input Power without damage	-50 dBm	-80 dBm
Output Power	≥ 20 dBm	
Spurious Emission (900-1GHz)	≤ -36dBm	≤ -36dBm
Spurious Emission (1GHz-12.75GHz)	≤ -30dBm	≤ -30dBm
Noise Figure @ Max. Gain	≤ 6dB (Typical)	
Return Loss	≤ 3dB	
Time Delay	≤ 0.5µs	
MTBF	> 50000hours	
Power Supply	DC 12V 2A	
Power Consumption	< 10 Watt	
Impedance	50 ohm	

#### Mechanical Specifications

RF Connector	N-Female
Cooling	Heatsink convection cooling
Dimensions (DxWxH)	178 x 234 x 24 mm
Weight	1120 Gram
Environment Conditions	IP-40
Humidity	< 90%
Operating Temperature	-10C - 60C